

System Studies Incorporated



2-1340 East Cliff Drive
 Santa Cruz, CA 95062
 (831) 475-5777
 (800) 247-8255
 (831) 475-9207 FAX
 www.airtalk.com

Resistive Flow Transducer Conversion Chart					
0 - 10 (SCFH)	0 - 19 (SCFH)	0 - 50 (SCFH)	0 - 100 (SCFH)	Electrical Resistance (KILOHMS)	Voltmeter Reading 120V Scale
0.0	0.0	0.0	0.0	3820	2.5
0.5	1.0	2.6	5.3	1820	5.0
1.0	2.0	5.3	10.5	1200	7.5
1.5	3.0	7.9	15.8	898	10.0
2.0	4.0	10.5	21.0	698	12.5
2.5	5.0	13.2	26.3	568	15.0
3.0	6.0	15.8	31.6	468	17.5
3.5	7.0	18.4	36.8	400	20.0
4.0	8.0	21.0	42.1	344	22.5
4.5	9.0	23.7	47.4	301	25.0
5.0	10.0	26.3	52.6	265	27.5
5.5	11.0	28.9	57.9	232	30.0
6.0	12.0	31.6	63.1	208	32.5
6.5	13.0	34.2	68.4	186	35.0
7.0	14.0	36.8	73.7	166	37.5
7.5	15.0	39.5	78.9	150	40.0
8.0	16.0	42.0	84.2	135	42.5
8.5	17.0	44.7	89.5	122	45.0
9.0	18.0	47.3	94.7	110	47.5
9.5	19.0	50.0	100.0	100	50.0